

For example, you can use curl in your Linux script as follows:

```
curl http://192.168.1.77/relays.htm?s1=4 &s0      // this selects V4 and enables Relay  
4 control  
curl http://192.168.1.77/relays.htm?s1=4          // this selects V4 but disables Relay  
4 control
```

Here is a list of GET requests for enabling/disabling voltage control:

Relay 1 Control:

```
http://192.168.1.77/relays.htm?d1=1&d0 // Relay 1 - V1 control enabled  
http://192.168.1.77/relays.htm?d1=1 // Relay 1 - V1 control disabled  
http://192.168.1.77/relays.htm?d1=2&d0 // Relay 1 - V2 control enabled  
http://192.168.1.77/relays.htm?d1=2 // Relay 1 - V2 control disabled  
http://192.168.1.77/relays.htm?d1=3&d0 // Relay 1 - V3 control enabled  
http://192.168.1.77/relays.htm?d1=3 // Relay 1 - V3 control disabled  
http://192.168.1.77/relays.htm?d1=4&d0 // Relay 1 - V4 control enabled  
http://192.168.1.77/relays.htm?d1=4 // Relay 1 - V4 control disabled
```

Relay 2 Control:

```
http://192.168.1.77/relays.htm?i1=1&i0 // Relay 2 - V1 control enabled  
http://192.168.1.77/relays.htm?i1=1 // Relay 2 - V1 control disabled  
http://192.168.1.77/relays.htm?i1=2&i0 // Relay 2 - V2 control enabled  
http://192.168.1.77/relays.htm?i1=2 // Relay 2 - V2 control disabled  
http://192.168.1.77/relays.htm?i1=3&i0 // Relay 2 - V3 control enabled  
http://192.168.1.77/relays.htm?i1=3 // Relay 2 - V3 control disabled  
http://192.168.1.77/relays.htm?i1=4&i0 // Relay 2 - V4 control enabled  
http://192.168.1.77/relays.htm?i1=4 // Relay 2 - V4 control disabled
```

Relay 3 Control:

```
http://192.168.1.77/relays.htm?n1=1&n0 // Relay 3 - V1 control enabled  
http://192.168.1.77/relays.htm?n1=1 // Relay 3 - V1 control disabled  
http://192.168.1.77/relays.htm?n1=2&n0 // Relay 3 - V2 control enabled  
http://192.168.1.77/relays.htm?n1=2 // Relay 3 - V2 control disabled  
http://192.168.1.77/relays.htm?n1=3&n0 // Relay 3 - V3 control enabled  
http://192.168.1.77/relays.htm?n1=3 // Relay 3 - V3 control disabled  
http://192.168.1.77/relays.htm?n1=4&n0 // Relay 3 - V4 control enabled  
http://192.168.1.77/relays.htm?n1=4 // Relay 3 - V4 control disabled
```

Relay 4 Control:

```
http://192.168.1.77/relays.htm?s1=1&s0 // Relay 4 - V1 control enabled  
http://192.168.1.77/relays.htm?s1=1 // Relay 4 - V1 control disabled  
http://192.168.1.77/relays.htm?s1=2&s0 // Relay 4 - V2 control enabled  
http://192.168.1.77/relays.htm?s1=2 // Relay 4 - V2 control disabled  
http://192.168.1.77/relays.htm?s1=3&s0 // Relay 4 - V3 control enabled
```

<http://192.168.1.77/relays.htm?s1=3> // Relay 4 - V3 control disabled  
<http://192.168.1.77/relays.htm?s1=4&s0> // Relay 4 - V4 control enabled  
<http://192.168.1.77/relays.htm?s1=4> // Relay 4 - V4 control disabled